

Congratulation for purchasing the high quality Vape ignition kit for your Lambretta! Wiring it up is dead easy and very similar to all other electronic ignitions for the Lambretta.

### Setting it up using an AC regulator

**YELLOW** wire gives the AC current that goes to the regulator.

**BLACK** wire from stator plate is earth wire. Connecting it to the regulator makes sense, but can be go to all other good earth points.

**RED** wire goes from the stator to the CDI.

**BLUE** wire from the CDI is connected to the green wire from the ignition or kill switch.

**BROWN** wire is connected to earth.\*

**BLACK** wire from CDI is connected to earth.\*

*\*ATTENTION: a good and solid connection of the CDI to earth is essential on the VAPE ignition, otherwise the CDI might be damaged!*

